

Unity Connection HQ MWI Restrictions

« InterSite VoiceMail between HQ/SiteB/SiteC (</workbook/view/ccie-collaboration/task/intersite-voicemail-between-hq-siteb-sitec-MzA3OA%3D%3D>) | Integration on UCCX with CallManager (</workbook/view/ccie-collaboration/task/integration-on-uccx-with-callmanager-MzA4MA%3D%3D>) »

Last updated: November 13, 2017


CONTENTS >

Tasks

- HQ Phones should not be able to trigger MWI on and off by dialing 1998 and 1999 numbers.

Configuration: [Click to collapse](#)

Call Routing > Class of Control > Partition



Call Routing > Class of Control > Calling Search Space

Calling Search Space Configuration

Save Delete Copy Add New

Status
Status: Ready

Calling Search Space Information
Name*: CSS-MWI
Description:

Route Partitions for this Calling Search Space

Available Partitions**
Directory URI
PT-2801-MEETME
PT-CalledXform
PT-CallingXform-SNR
PT-Common

Selected Partitions
PT-MWI

Save Delete Copy Add New

Message Waiting Numbers (1 - 2 of 2)

Directory Number	Description	Partition	Calling Search Space
1998		PT-MWI	CSS-MWI
1999		PT-MWI	CSS-MWI

Find and List Voice Mail Ports							
Add New Select All Clear All Delete Selected Reset Selected Apply Config to Selected							
Status 3 records found							
Voice Mail Port (1 - 3 of 3)							
Find Voice Mail Port with Device Name begins with <input type="text"/> <input type="button" value="Find"/> <input type="button" value="Clear Filter"/> <input type="button" value="↕"/> <input type="button" value="⇌"/>							
Select item or enter search text							
<input type="checkbox"/>	Device Name ^	Description	Device Pool	Device Security Mode	Calling Search Space	Extension	Partition
<input type="checkbox"/>	CiscoUM1-V11	DP-Phones	Non Secure Voice Mail Port	CSS-MWI		2221	
<input type="checkbox"/>	CiscoUM1-V12	DP-Phones	Non Secure Voice Mail Port	CSS-MWI		2222	
<input type="checkbox"/>	CiscoUM1-V13	DP-Phones	Non Secure Voice Mail Port	CSS-MWI		2223	

Verification

Call from HQ Phones 1998 and 1999 you should not be able to dial these numbers.
 Leave voicemail from Site B/Site C/HQ Phones and test MWI triggers when VM is left.

« [InterSite VoiceMail between HQ/SiteB/SiteC \(/workbook/view/ccie-collaboration/task/intersite-voicemail-between-hq-siteb-sitec-MzA3OA%3D%3D\)](#) | [Integration on UCCX with CallManager \(/workbook/view/ccie-collaboration/task/integration-on-uccx-with-callmanager-MzA4MA%3D%3D\)](#) »