

CCIE Collaboration (<http://labs.ine.com/workbook/toc/ccie-collaboration>) » Cisco IOS UC Applications & Features

## CUCME SIP Phones Registration (VOICE REGISTER GLOBAL)

« SCCP (Skinny) Phones Registration (TELEPHONY-SERVICE) (/workbook/view/ccie-collaboration/task/sccp-skinny-phones-registration-telephony-service-MzA2MA%3D%3D) | IOS DialPlan (/workbook/view/ccie-collaboration/task/ios-dialplan-MzA2Mg%3D%3D) »

Last updated: November 10, 2017

CONTENTS >

---

### Tasks

- Register and Configure Site C Phone 2 according to the provided telephony number scheme.
  - This phone should display globalized calling number, "+85270044002", on the top right hand side corner.
  - Extension-to-Extension dialing at each site uses the last four digits only, calling name display should be delivered on internal 4-digits calls use trivial caller names such as "Site C Phone 2".
  - Make sure the phone displays the correct local time in 24 hour format and date display is arranged as D/M/Y.
  - Lastly enable the video and camera on this phone.

### Configuration: [Click to collapse](#)

Site C - R3

```
voice register global
  mode cme
  source-address 11.102.66.254
  max-dn 20
  max-pool 10
  timeouts interdigit 5
  timezone 42
  date-format D/M/Y
  time-format 24
  create profile
!
voice register dn 1
  number 4002
  name Site C Phone 2
!
voice register pool 1
  id mac XXXX.XXXX.XXXX
  description +85270004002
  type 9971
  number 1 dn 1
  camera
  video
!
voice service voip
  sip
  registrar server
```

## Verification

### On Site C - R3

```
show voice register pool 1
```

« SCCP (Skinny) Phones Registration (TELEPHONY-SERVICE) (/workbook/view/ccie-collaboration/task/sccp-skinny-phones-registration-telephony-service-MzA2MA%3D%3D) | IOS DialPlan (/workbook/view/ccie-collaboration/task/ios-dialplan-MzA2Mg%3D%3D) »