

CUCME Conference Meet-Me

« CUCME Media Resources - Conference Ad-Hoc (</workbook/view/ccie-collaboration/task/cucme-media-resources-conference-ad-hoc-MzA2NQ%3D%3D>) | Site C CUCME Features - Single Number Reach for SCCP Phone (</workbook/view/ccie-collaboration/task/site-c-cucme-features-single-number-reach-for-sccp-phone-MzA2Nw%3D%3D>) »

Last updated: November 10, 2017

Tasks

- Site C Hardware conference resource should also provide meet-me services. All local Site C IP Phones should be able to initiate the Meet-Me conference on 4020.
- Allow any PSTN callers to join the conference by dialing 70044020 along with Site B and HQ Phones.
- Provision the 6th button on both Site C Phone 1 & Site C Phone 2 to be equivalent of Meet-Me key.
- Also for Site C Phone 1 configure Meet-Me softkey.

Configuration: [Click to collapse](#)

Site C - R3

```
ephone-dn 19 octo-line
  number 4020
  conference meetme
!
ephone-template 1
  softkeys seized Redial Endcall Cfwdall Pickup Gpickup Callback Meetme
  feature-button 1 MeetMe
  button-layout 1 line
  button-layout 6 feature
!
ephone 1
  ephone-template 1
  reset
!
voice register template 1
  feature-button 1 MeetMe
  button-layout 1 line
  button-layout 6 feature-button
!
voice register pool 1
  template 1
  reset
!
telephony-service
  create cnf-files
!
voice register global
  create profile
```

Verification

From Site C Phone 1 go on speaker hit the 6th line of Meet-Me and dial 4020

From Site C Phone 2/PSTN/Site B/HQ join the Meet-me conference

« CUCME Media Resources - Conference Ad-Hoc (/workbook/view/ccie-collaboration/task/cucme-media-resources-conference-ad-hoc-MzA2NQ%3D%3D) | Site C CUCME Features - Single Number Reach for SCCP Phone (/workbook/view/ccie-collaboration/task/site-c-cucme-features-single-number-reach-for-sccp-phone-MzA2Nw%3D%3D) »