

CCIE Collaboration (<http://labs.ine.com/workbook/toc/ccie-collaboration>) » Cisco IOS UC Applications & Features

CME SIP Phone Security Administration

« Video Conferencing (</workbook/view/ccie-collaboration/task/video-conferencing-MzA2OQ%3D%3D>) | CME Fast Dials/Speed Dials & Local Directory (</workbook/view/ccie-collaboration/task/cme-fast-dials-speed-dials-local-directory-MzA3MQ%3D%3D>) »

Last updated: November 10, 2017

Tasks

- The Cisco 9971 Phone 2 at Site C prompts administrator password on screen when you try to navigate to the **Administration settings** page. The Default password is cisco/Cisco
- Remove this password and allow direct access to the administrator setting page.
- To comply with your phone security policy of your company, you are required to disable PC port of Site C Phone 1 & Site C Phone 2.

Configuration: [Click to collapse](#)

On R3 Gateway (For Site C SIP Phone)

```
more flash:its/SEP204C9ED736A6.cnf.xml
```

Copy the file into notepad

Edit the file and search for below field and remove the password cisco/Cisco

```
<phonePassword></phonePassword>
```

Edit the vendorConfig xml field as below

```
<vendorConfig>
<pcPort>1</pcPort>
</vendorConfig>
```

On R3 Gateway (In Privilege Mode)

```
tclsh
puts [open flash:SEP204C9ED736A6.cnf.xml w+] {
PASTE THE FILE
}
tclquit
```

```
tclsh
puts [ open "flash:blank.cfg" w+] {
version 15.4
!
end
}
tclquit
```

```
tftp-server flash:SEP204C9ED736A6.cnf.xml
!
voice register pool 1
  reset
!
voice register global
  no create profile
```

On R3 Gateway (For Site C Skinny Phone)

```
telephony-service
  service phone pcPort 1
  create cnf-files
!
ephone 1
  reset
```

Note:

EVERYTIME YOU CREATE PROFILE IT REMOVES THE TFTP SERVER MAPPING YOU CREATED EARLIER AND WILL TAKE ORIGINAL .CNF.XML FILE FROM ITS FOLDER

Verification

Verify by clicking Settings on the 9971 phone and navigate to Administrator Settings. It should not prompt for the password.

Also check PcPort should show disabled.

« [Video Conferencing \(/workbook/view/ccie-collaboration/task/video-conferencing-MzA2OQ%3D%3D\)](/workbook/view/ccie-collaboration/task/video-conferencing-MzA2OQ%3D%3D) | [CME Fast Dials/Speed Dials & Local Directory \(/workbook/view/ccie-collaboration/task/cme-fast-dials-speed-dials-local-directory-MzA3MQ%3D%3D\)](#) »